

Naim Uniti Nova Specifications:

| | |
|-------------------------|--|
| DAB/FM | Optional DAB/FM module available (release date to be confirmed) |
| Memory Card | 1 x SD Card Max SD card storage: 32GB |
| Streaming | Chromecast Built-In, Apple AirPlay, TIDAL, Spotify® Connect, Bluetooth (AptX HD), Internet Radio, UPnP™ (hi-res streaming), Roon Ready |
| USB | 2 x USB Type A Socket (front and rear) External portable SSD – max. 1TB USB <i>sticks</i> – max. 128 GB. |
| Analogue | 1 x RCA 1 x 4-pin DIN |
| Digital (S/PDIF) | 2 x Optical TOSLink (up to 24bit/96kHz) 2 x Coaxial RCA (up to 24bit/192kHz, DoP 64Fs) 1 x BNC (up to 192kHz, DoP 64Fs) 1 x HDMI ARC |
| Analogue | 1 x Stereo power amplifier 1 x RCA sub/pre output 1 x 3.5mm headphone jack |
| Certification | Apple AirPlay, Chromecast Built-In, Bluetooth, AptX HD, zigbee RF4CE, Rovi, HDMI, NTFS, HFS and Wi-Fi. |
| Multiroom | Serve up to 4 network-connected players via UPnP™ at full CD quality. Party Mode Streaming: Sync up to six Uniti all-in-one players or other Naim streamers and control via the Naim app. |
| Updates | Update your system wirelessly via the Naim app. |
| Network | Ethernet (10/100Mbps), WiFi (802.11 b/g/n/ac with internal antennae) |
| Internet Radio Formats | Windows Media-formatted content, MP3, ACC, OGG Vorbis streams and MMS |
| Internet Radio Provider | vTuner premium 5* |

| | |
|-------------------|--|
| Audio Formats | <p>WAV - up to 32bits/384kHz FLAC and AIFF - up to 24bit/384kHz ALAC (Apple Lossless) - up to 24bit/384kHz MP3 - up to 48kHz, 320kbit (16 bit) AAC - up to 48kHz, 320kbit (16 bit) OGG and WMA - up to 48kHz (16 bit) DSD - 64 and 128Fs Notes: Gapless playback supported on all formats. All formats to 384kHz maximum over wireless network.</p> |
| Dimensions | 95mm x 432mm x 265mm (HxWxD) |
| Finishes | Brushed and anodised aluminium |
| Weight | 13kg |
| Auto Standby time | User selectable: adjustable from off up to 2 hours |
| Amplifier Output | 80W per channel into 8 ohms |
| Mains Supply | 115V, 230V; 50 or 60Hz |
| Power Consumption | <p>Typical use: 140W Network standby mode: <2W Deep sleep: <0.5W Network Standby (with SD Card and/or USB devices attached): > 15W*. *Actual power consumption will vary depending on the size and type of attached SD card or USB devices</p> |
| Storage | <p>Store up to 20,000 tracks to a local USB connected storage device and serve to a network-connected player. External portable SSD – max. 1TB USB <i>sticks</i> – max. 128 GB.</p> |
| Supplied with | Remote control, Power-Line Lite mains cable (UK denominations only), cleaning cloth and quick start guide. |

| | |
|---------------|---|
| Mains Cable | Power-Line mains cable |
| Amplification | External power amplifier or sub-woofer |
| App Control | Naim App for iOS and Android |
| Front Panel | 5"" colour LCD display and rotary volume control with proximity sensor and four buttons |
| Handheld | zigbee RF4CE |